

_Bridge-Gate B to G h i - r e z USB to spdif adaptor
MODELLO : B to G USB - S P D I F



The Bridge-Gate usb to spdif adaptor convert the computer output USB (V-1/2/3) to spdif IEC-958 standard.

The adaptor is native with OSX (apple) and Linux S.O. no need install any driver.

For windows (vista/xp/7/8/8.1) we supply right and stable driver at 32 and 64 bit.

The unit support also ASIO driver, included on cd rom.

Converter accept frequency from 44.1 / 48 / 88.2 / 96 /176.4 /192 Khz at 16 and 24 bit.

Front panel offer function as: led on when the unit is connected with usb pc port, mute power switch.

Rear panel offer input for USB standar type A and two spdif output as RCA and BNC connectors.

Frequency as low resolution as 44.1 and 48.0 Khz , the BtoG turn into a output as 88.2 and 96 Khz for better sound and quality performances for get max resolution on your DAC !

Performances

Unit description : **USB to SPDIF convertor**

Input: **USB Vers. 1.1/2/3**

Output: **Spdif by RCA and BNC connectors**

Standard output : **IEC-958 400 mV**

Input digital sampling : **44.1/48/88.2/96/176.4/192**

Resolution : **16 and 24 bit**

Output isolation : **Pulse digital transformer**

Power supply : **From PC USB port low noise device**

Dimension and weight: **200 (L) 4.5 (H) 150 (D) mm KG.1**

Certification : **CE-EMC / CE-LVD / IEC-65**

Docet digital hi-fi
Via Assi San Paolo,6
27100 Pavia (PV) Italy

tel. +39 (0) 382 481022

Fax +39 (0) 382 481021

Email: infoaudio@docethifi.com

Web:www.docethifi.com

DOCET

